



# SUBSTITUTE SPECIFICATION

TITLE OF THE INVENTION

COMMUNICATIONS CONTROL METHOD

BACKGROUND OF THE INVENTION

5 1. Field of the Invention

[0001] The present invention relates to communications control methods and, more specifically, to a method for controlling communications among a plurality of terminals coupled to each other to form a network for serial transmission of a mixture of isochronous  
10 data and anisochronous data.

2. Description of the Background Art

[0002] In recent years, computers, peripheral devices, digital video devices, and other components are often connected to each  
15 other in homes and offices to form a local area network. On the network of this type, a mixture of isochronous data recurring at periodic time intervals (for example, video and audio data for streaming reproduction) and anisochronous data (for example, burst-like communications data) is transmitted in serial.

20 [0003] One example of the known standards for serial transmission of such a mixture is IEEE 1394. In IEEE 1394, all components forming a network are under communications control as described below.

[0004] FIG. 23 is a diagram showing an example of the structure  
25 of a conventional local-area network 209 that complies with the

IEEE 1394 standard. FIG. 24 is a schematic diagram showing a conventional communications control method according to the IEEE 1394 standard. An example of the structure of a communications control cycle according to the IEEE 1394 standard is shown in (A) of FIG. 24, and an example of communications control carried out on the network of FIG. 23 is shown in (B) of FIG. 24.

[0005] In FIG. 23, the conventional network 209 includes a controller 210, a digital video player 211, a digital television 212, a set-top box (hereinafter, STB) 213, and a computer 214. These components 210 to 214 are connected in serial (or in tree shape) to each other via a cable that complies with IEEE 1394. In the network 209, the controller 210 controls the other components 211 to 214.

[0006] In the above structured network 209, assume herein that isochronous data "I1" is going to be transmitted from the digital video player 211 to the digital television 212; isochronous data "I2" is going to be transmitted from the STB 213 to the computer 214; and anisochronous data "N" is going to be transmitted from the computer 214 to the digital video player 211.

[0007] In IEEE 1394, as shown in (A) of FIG. 24, a control time is divided into predetermined cycles (for example, every 125  $\mu$ s), and each cycle has a predetermined isochronous region of a predetermined time length (for example, 100  $\mu$ s at maximum). The isochronous region is further divided into plural (two, in this example) regions. These two regions are respectively assigned

to the components having isochronous data to be transmitted. In the example, one divided region is assigned, as a dedicated region (channel 1), to the digital television 212, while the other divided region is assigned, as a dedicated region (channel 2), to the STB 213.

**[0008]** As shown in (B) of FIG. 24, before the start of transmission, the controller 210 reports, to each component, information 200 about the dedicated regions assigned to these components. The information 200 includes times when each isochronous data is to be transmitted. When transmission starts and enters into the cycle, the controller 210 first transmits a packet 201 indicating the start of the cycle to each component. Upon receiving the cycle start packet 201, the components having the isochronous data to be transmitted (here, the digital video player 211 and the STB 213) transmit the isochronous data (I1 and I2, respectively) by using the dedicated region of their own (channel 1 and channel 2, respectively).

**[0009]** When the procedure exits the isochronous region, the controller 210 provides a transmission instruction 202 to the component having the anisochronous data (here, the computer 214). Upon receiving the instruction from the controller 210, the computer 214 transmits the anisochronous data (N).

**[0010]** Next, the destination of the anisochronous data (N) (here, the digital video player 211) receives the anisochronous data, and then returns a response packet 203 indicating whether or not

the data has been successfully received, to the data originating terminal (the computer 214) and the controller 210. Upon receiving the response packet 203 from the computer 214, the controller 210 determines whether or not retransmission is required. In this  
80 example, the transmitted response packet 203 indicates that the data has been successfully received. Therefore, the controller 210 determines that retransmission is not required. Then, when the procedure exits the cycle and then enters into another, the controller transmits a packet indicating the start of the next  
85 cycle to each terminal (such packet transmission procedure is not shown in FIG. 24), and then the procedure is repeated similarly thereafter.

**[0011]** On the other hand, if the response packet 203 returned from the digital video player 211 indicates a reception error,  
90 the controller 210 transmits, to the computer 214, an instruction for retransmitting the anisochronous data (N). Then, the digital video player 211 returns response packets to the computer 214 and the controller 210. If the response packet from the digital video player 211 indicates a reception error, the controller 210 again  
95 instructs the computer 214 to retransmit the data (such retransmission procedure is not shown in FIG. 24).

**[0012]** As such, according to the IEEE 1394 standard, the control time is divided into cycles, and each cycle has an isochronous region of a predetermined time length allocated. This isochronous  
100 region is further divided into dedicated regions to be assigned

to the components having isochronous data. Therefore, each of these components can transmit the isochronous data one time per cycle. Consequently, the isochronous characteristics can be kept.

105   **[0013]**     On the other hand, the region other than the isochronous region in each cycle is an anisochronous region, where the components having anisochronous data to be transmitted are controlled (asynchronous control) so that they carry out transmission one after the other. Thus, serial transmission of  
110 mixed isochronous and anisochronous data can be achieved.

**[0014]**     In IEEE 1394, even if a reception error of the isochronous data occurs, retransmission control is not carried out. Instead, the ratio of error occurrence is reduced to less than a predetermined value by restricting the length of a cable connecting the components  
115 together to less than a predetermined length (4.5m if a conductor cable). With the ratio of error occurrence less than the predetermined value, quality deterioration in image and sound can be suppressed to such an extent that the user cannot recognize the deterioration.

120   **[0015]**     In recent years, a wireless connection between components has become more desired. A wireless connection dispenses with the time and trouble of wiring, and enables the user to use each component wherever he/she desires.

**[0016]**     In a wireless transmission path, however, transmission  
125 errors are prone to occur more, as compared with a wired transmission

path. The ratio of transmission error occurrence is significantly increased if the components are spaced far apart or an obstacle is located therebetween. As a result, it is highly possible that images may be disturbed during streaming reproduction and noise  
130 may be mixed in sound.

#### SUMMARY OF THE INVENTION

**[0017]** Therefore, an object of the present invention is to provide a communications control method used in the serial  
135 transmission of a mixture of isochronous data and anisochronous data for preventing image disturbances during streaming reproduction and noise mixed in sound even though a transmission path with a high ratio of occurrence of transmission errors is used for communications.

140 **[0018]** The present invention has the following features to attain the above object.

**[0019]** A first aspect of the present invention is directed to a method for controlling communications among a plurality of terminals coupled to each other to form a network in which a mixture  
145 of isochronous data and anisochronous data is serially transmitted. The communications control method includes: a step of dividing time into cycles, and providing an isochronous region and an anisochronous region for each cycle; a step of, after each terminal transmits, for each cycle, the isochronous data using the  
150 isochronous region in a time division manner, determining by a

destination terminal whether or not the isochronous data has been successfully received; and a step of, when there is any terminal that has not successfully received the isochronous data, instructing an originating terminal of the isochronous data to  
155 retransmit the isochronous data by using the anisochronous region.

**[0020]** In the above first aspect, the isochronous data that has not been successfully received is retransmitted by using the anisochronous region. Therefore, a transmission error of the isochronous data can be reduced without impairment of isochronous  
160 characteristics. As a result, image disturbances during streaming reproduction and noise mixed in sound can be prevented even if the transmission path between the terminals is the one with a high ratio of occurrence of transmission errors, such as a wireless transmission path.

165 **[0021]** According to a second aspect, in accordance with the first aspect, each terminal transmits the isochronous data with an error detection code added thereto and the destination terminal checks the error detection code after receiving the isochronous data, and the determination step is performed based on a check  
170 result.

**[0022]** In the above second aspect, the destination terminal of the isochronous data transmits a result of checking the error detection code added to the isochronous data. Based on the result, it can whether determined or not the isochronous data has been  
175 successfully received can.

[0023] According to a third aspect, in accordance with the first aspect, each terminal transmits the isochronous data as being divided into blocks, the determination step is performed for each block, and the instructing step is performed for each block.

180 [0024] In the above third aspect, the isochronous data is transmitted as being divided into blocks. Therefore, when an error occurs in only part of the received data, only the block that has the error is retransmitted. Consequently, retransmission time is reduced. Thus, the possibility that retransmission of the  
185 isochronous data using the anisochronous region may consume time for transmitting the anisochronous data can be further prevented.

[0025] If there are a plurality of terminals that have not successfully received the isochronous data, such control as indicated by the following fourth and fifth aspects is carried  
190 out.

[0026] According to the fourth aspect, in accordance with the first aspect, in the instructing step, when there are the terminals that have not successfully received the isochronous data, the originating terminals of the isochronous data are sequentially  
195 instructed to retransmit the isochronous data by using the anisochronous region in the time division manner.

[0027] According to the fifth aspect, in accordance with the first aspect, in the instructing step, when there are the terminals that have not successfully received the isochronous data,  
200 transmission times are collectively reported to the originating



terminals of the isochronous data so that the originating terminals retransmit the isochronous data by using the anisochronous region in the time division manner.

**[0028]** In the fourth and fifth aspects, the isochronous data  
205 can be retransmitted by each terminal using the anisochronous region in a time division manner.

**[0029]** According to a sixth aspect, in accordance with the first aspect, each terminal modulates the isochronous data before transmission, and, in the instructing step, the originating  
210 terminal is instructed to retransmit the isochronous data after changing a modulation scheme used in modulation.

**[0030]** According to a seventh aspect, in accordance with the first aspect, each terminal encodes the isochronous data before transmission, and, in the instructing step, the originating  
215 terminal is instructed to retransmit the isochronous data after changing a coding rate used in encoding.

**[0031]** According to an eighth aspect, in accordance with the first aspect, each terminal encodes and modulates the isochronous data before transmission, and, in the instructing step, the  
220 originating terminal is instructed to retransmit the isochronous data after changing a coding rate used in encoding and a modulation scheme used in modulation.

**[0032]** In the above sixth to eighth aspects, the ratio of reoccurrence of transmission errors at retransmission can be  
225 further prevented. As a result, the number of times of

retransmission is reduced, and thus the possibility that repetitive retransmission may consume time of transmitting the anisochronous data can be further prevented.

**[0033]** According to a ninth aspect, in accordance with the first  
230 aspect, each terminal carries out multicast transmission of the isochronous data to the terminals that belong to respective specific groups; in the determination step, it is determined whether or not the isochronous data has been successfully received by all terminals that belong to the group destined to receive the  
235 isochronous data; and in the instructing step, when there is one or more terminals in the group that have not successfully received the isochronous data, the originating terminal is instructed to carry out multicast retransmission of the isochronous data to all of the terminals that belong to the group.

240 **[0034]** In the above ninth aspect, even on a network where each terminal carries out multicast transmission, transmission errors of the isochronous data can be reduced without impairment of isochronous characteristics.

**[0035]** According to a tenth aspect, in accordance with the first  
245 aspect, each terminal carries out broadcast transmission of the isochronous data to all of other terminals; in the determination step, it is determined whether or not the isochronous data has been successfully received by all terminals destined to receive the isochronous data; and in the instructing step, when there is  
250 one or more terminals that have not successfully received the

isochronous data, the originating terminal is instructed to carry out broadcast retransmission of the isochronous data to all of the terminals.

**[0036]** In the above tenth aspect, even on a network where each terminal carries out broadcast transmission, transmission errors of the isochronous data can be reduced without impairment of isochronous characteristics.

**[0037]** According to an eleventh aspect, in accordance with the first aspect, the communications control method further includes the step of dividing the isochronous region into dedicated regions, assigning the dedicated regions to the respective terminals, and reporting, to each terminal, information about the dedicated region before a start of a head of the cycle, thereby enabling transmission of the isochronous data for each cycle by each terminal using the isochronous region in the time division manner.

**[0038]** In the above eleventh aspect, the dedicated region information is reported to each terminal before the start of the head cycle. By referring to the dedicated region information, each terminal transmits, for each cycle, the isochronous data at the time corresponding to the dedicated region assigned to itself.

**[0039]** According to a twelfth aspect, in accordance with the first aspect, the communications control method further includes the step of dividing the isochronous region into dedicated regions, assigning the dedicated regions to the respective terminals, and sequentially instructing, for each cycle at respective times

corresponding to the dedicated region, the terminals to transmit the isochronous data, thereby enabling transmission of the isochronous data for each cycle by each terminal using the isochronous region in the time division manner.

280 **[0040]** In the above twelfth aspect, the terminals are sequentially instructed, for each cycle, to carry out transmission at the time corresponding the dedicated region. In response to the instruction, each terminal transmits the isochronous data.

**[0041]** According to a thirteenth aspect, in accordance with  
285 the first aspect, the communications control method further includes the step of giving an inquiry to the destination terminal about whether or not the isochronous data has been successfully received, wherein the determination step is carried out based on a response to an inquiry.

290 **[0042]** In the above thirteenth aspect, the destination terminal is inquired about whether or not reception has succeeded.

**[0043]** According to a fourteenth aspect, in accordance with the first aspect, the destination terminal spontaneously gives a response about whether or not the isochronous data has been  
295 successfully received, and the determination step is carried out based on the response.

**[0044]** In the above fourteenth aspect, the destination terminal spontaneously reports whether or not reception has succeeded.

**[0045]** According to a fifteenth aspect, in accordance with the  
300 first aspect, the instructing step is carried out repetitively

until the isochronous data is successfully received.

**[0046]** In the above fifteenth aspect, retransmission is repeated until a reception error is cleared.

**[0047]** According to a sixteenth aspect, in accordance with the  
305 fifteenth aspect, the communications control method further includes the step of suspending retransmission of the isochronous data even though a reception error is not cleared when a time consumed by one more retransmission presumably exceeds a predetermined maximum time allowed, for each cycle, to be consumed for  
310 retransmitting the isochronous data.

**[0048]** In the above sixteenth aspect, the retransmission time of the isochronous data is limited to less than a predetermined value. Thus, the possibility that retransmission may impair the isochronous characteristics of the data or consume time for  
315 transmitting the anisochronous data is prevented.

**[0049]** According to a seventeenth aspect, in accordance with the sixteenth aspect, the maximum time is less in value than a time length of the anisochronous region.

**[0050]** In the above seventeenth aspect, retransmission of the  
320 isochronous data carried out in the isochronous region of the next cycle can be prevented. Therefore, impairment of the isochronous characteristics of the data can be prevented.

**[0051]** According to an eighteenth aspect, in accordance with the seventeenth aspect, the maximum time is equal in value to a  
325 time length of the anisochronous region.

[0052] In the above eighteenth aspect, the entire anisochronous region can be used for the retransmission of the isochronous data. Thus, a transmission error of the isochronous data can be most effectively reduced.

330 [0053] According to a nineteenth aspect, in accordance with the seventeenth aspect, the communications control method further includes the step of retransmitting, in the anisochronous region of a next cycle, the isochronous data whose retransmission is suspended.

335 [0054] In the above nineteenth aspect, suspended retransmission of the isochronous data is restarted after the procedure enters into the anisochronous region of the next cycle.

[0055] According to a twentieth aspect, in accordance with the fifteenth aspect, the communications control method further  
340 includes the step of suspending retransmission of the isochronous data even though a reception error is not cleared when the number of times of retransmission exceeds a predetermined maximum number of times of retransmission of the isochronous data.

[0056] In the above twentieth aspect, an infinite repetition  
345 of retransmission of the same isochronous data can be prevented.

[0057] A twenty-first aspect of the present invention is directed to a communications control apparatus for controlling communications among a plurality of terminals coupled to each other to form a network in which a mixture of isochronous data and  
350 anisochronous data is serially transmitted. The communications

control apparatus includes: a part for dividing time into cycles,  
and providing an isochronous region and an anisochronous region  
for each cycle; a part for, after each terminal transmits, for  
each cycle, the isochronous data using the isochronous region in  
355 a time division manner, determining by a destination terminal  
whether or not the isochronous data has been successfully received;  
and a part for, when there is any terminal that has not successfully  
received the isochronous data, instructing an originating terminal  
of the isochronous data to retransmit the isochronous data by using  
360 the anisochronous region.

**[0058]** A twenty-second aspect of the present invention is  
directed to a computer-processable program having a method such  
as that according to the above first aspect written thereon.

**[0059]** A twenty-third aspect of the present invention is  
365 directed to a recording medium having a program such as that  
according to the above twenty-second aspect stored thereon.

**[0060]** These and other objects, features, aspects and  
advantages of the present invention will become more apparent from  
the following detailed description of the present invention when  
370 taken in conjunction with the accompanying drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS

**[0061]** FIG. 1 is a schematic diagram for demonstrating a  
communications control method according to a first embodiment of  
375 the present invention, where (A) of FIG. 1 illustrates an example

of the structure of a communications control cycle and (B) of FIG. 1 illustrates an example of communications control carried out in a wireless local-area network 9 of FIG. 2;

FIG. 2 is a diagram showing an example of the structure  
380 of the network 9 to which the method of FIG. 1 is applied;

FIG. 3 is a diagram showing an example of the structure of a wireless communications module 20 provided in each component (10 to 14) of FIG. 2;

FIG. 4 is a diagram showing the contents of a program  
385 memory 24 of FIG. 3;

FIG. 5 is a schematic diagram, in relation to (B) of FIG. 1, for demonstrating retransmission control carried out when isochronous data (block) has not been successfully received;

FIG. 6 is a diagram, in relation to (B) of FIG. 1, showing  
390 the state where retransmission of isochronous data is suspended even if a reception error is not solved;

FIG. 7 is a flowchart showing the operation of a controller 10 (control station) of FIG. 2;

FIG. 8 is a diagram showing one example of dedicated  
395 region information reported to each terminal in step S5 of FIG. 7;

FIG. 9 is a flowchart showing the operation of each terminal (11 to 14) of FIG. 2;

FIG. 10 is a flowchart showing detailed transmission processing of isochronous data shown in step S22 of FIG. 9;

400 FIG. 11 is a flowchart showing detailed data reception



processing shown in step S26 of FIG. 9;

FIG. 12 is a diagram showing an example of the structure of a response packet transmitted in step S63 of FIG. 11;

FIG. 13 is a diagram showing the state where isochronous  
405 data whose retransmission is suspended based on the determination result in step S8 of FIG. 7 is retransmitted at a next anisochronous region of the next cycle;

FIG. 14 is a schematic diagram for demonstrating a communications control method according to a second embodiment  
410 of the present invention;

FIG. 15 is a schematic diagram for demonstrating a communications control method according to a third embodiment of the present invention;

FIG. 16 is a diagram showing the contents of a global  
415 polling packet 90 being multicast by the control station;

FIG. 17 is a diagram showing the contents of a global retransmission request packet 95 being multicast by the control station;

FIG. 18 is a schematic diagram showing a communications  
420 control method according to a fourth embodiment of the present invention;

FIG. 19 is a schematic diagram showing a communications control method according to a fifth embodiment of the present invention, where (A) of FIG. 19 illustrates an example of the  
425 structure of a communications control cycle and (B) of FIG. 19

illustrates an example of communications control carried out on the network 9 of FIG. 2;

FIG. 20 is a flowchart showing the operation of the control station 10 of FIG. 2 according to the fifth embodiment;

430        FIG. 21 is a flowchart showing the detailed processing of transmitting isochronous data shown in step S22 of FIG. 9, according to the fifth embodiment;

FIG. 22 is a diagram, in relation to (B) of FIG. 19, showing a communications control method of spontaneous  
435        transmission of a response packet when each terminal receives isochronous data;

FIG. 23 is a diagram showing an example of the structure of a conventional local-area network that complies with the IEEE 1394 standard; and

440        FIG. 24 is a schematic diagram for demonstrating a conventional communications control method according to the IEEE 1394 standard, where (A) of FIG. 24 illustrates an example of the structure of a communications control cycle according to IEEE 1394 and (B) of FIG. 24 illustrates an example of communications control  
445        carried out on a network 209 of FIG. 23.

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

### First Embodiment

**[0062]**        FIG. 1 is a schematic diagram for demonstrating a  
450        communications control method according to a first embodiment of

the present invention. FIG. 2 is a diagram illustrating an example of the structure of a wireless local area network 9 to which the method of FIG. 1 is applied. In FIG. 2, the wireless local area network 9 includes a controller 10, a digital video player 11, a digital television 12, a set-top box (hereinafter, STB) 13, and a computer 14. These components 10 to 14 are wirelessly coupled to each other. This network 9 is almost the same as the network 209 of FIG. 23 (refer to Background Art section), except that the ratio of occurrence of transmission errors is high because of the wireless connection among the components 10 to 14. In the network 9, the controller 10 controls wireless communications among the components 11 to 14.

**[0063]** Each of the components 10 to 14 forming the wireless local area network 9 is provided with a wireless communications module. An example of the structure of the wireless communications module is shown in FIG. 3. In FIG. 3, a wireless communications module 20 includes an antenna 21, a modulation/demodulation circuit 22, a processing circuit 23, a program memory 24, and an input/output circuit 25.

**[0064]** The antenna 21 converts a signal into an electric wave for emission and also acquires an electric wave for conversion into a signal. The modulation/demodulation circuit 22 modulates/demodulates the signal. The input/output circuit 25 is connected to another input/output circuit (not shown) of any of the components 10 to 14 equipped with this module for transmitting

and receiving signals with the component.

**[0065]** The program memory 24 stores various programs. The processing circuit 23 includes a microcomputer that processes signals by following the programs stored in the program memory 24.

480 The contents of the program memory 24 are shown in FIG. 4.

**[0066]** In FIG. 4, the program memory 24 stores a main program 30, a control station program 31, and a terminal program 32. The main program 30 describes the basic procedure for the module carrying out wireless communications. The control station program 31 describes the procedure for the module as a control station controlling the communications among the components. The terminal program 32 describes the procedure for the module as a terminal carrying out communications. These procedures described in the respective programs are computer-processable.

490 **[0067]** The wireless communications module 20 equipped in the controller 10 is initially set so that the control station program 31 is first activated. The wireless communications module 20 equipped in any of the other components 11 to 14 is initially set so that the terminal program 32 is first activated. Note that, by changing the initial setting, it is possible to make the component such as the computer 14 or the STB 13 operate as a controller.

**[0068]** In the above structured network 9, assume herein that isochronous data "I1" is going to be transmitted from the digital video player 11 (first terminal) to the digital television 12 (second terminal); isochronous data "I2" is going to be transmitted

500

from the STB 13 (third terminal) to the computer 14 (fourth terminal); and anisochronous data "N" is going to be transmitted from the computer 14 (fourth terminal) to the digital video player 11 (first terminal). Here, the controller (control station) 10 controls communications among the components (first to fourth terminals) so that a mixture of the isochronous data recurring at periodic time intervals and anisochronous data can be serially transmitted.

**[0069]** Hereinafter, the controller 10 is referred to as "control station", and the components 11 to 14 are referred to as a "first to fourth terminals", respectively. In this communications control, as shown in (A) of FIG. 1, time is divided into predetermined cycles, and each cycle is provided with an isochronous region and anisochronous regions. Then, the isochronous region is further divided into plural (two, in this example) dedicated regions. These regions are respectively assigned, as Ch. 1 and Ch. 2, to the components having the isochronous data to be transmitted (first and third terminals).

**[0070]** Here, the time length of the isochronous region is determined based on the amount of the isochronous data to be transmitted per unit time, and is limited, however, to a predetermined value so that the transmission path is not totally occupied by the isochronous data. By way of example only, if one cycle is  $125\mu\text{sec}$ , the time length of the isochronous region is limited to not more than  $100\mu\text{sec}$ , for example.

[0071] Furthermore, the isochronous region is provided so as to be located a predetermined time apart from the head of the cycle. Therefore, two regions preceding and following the isochronous region in the cycle are the anisochronous regions.

530 [0072] Furthermore, the control station knows the amount of isochronous data to be transmitted from each terminal per unit time. Therefore, the control terminal divides the isochronous region into dedicated regions based on the amount of transmission from each terminal, and assigns these dedicated regions to the  
535 respective terminals.

[0073] An example of the structure of the communication control cycle is shown in (A) of FIG. 1. An example of communications control carried out on (in) the network 9 of FIG. 2 is shown in (B) of FIG. 1.

540 [0074] In the example of (A) of FIG. 1, each cycle has the isochronous region provided from  $5\mu\text{sec}$  away from the head of the cycle as the origin ( $0\mu\text{sec}$ ) to  $85\mu\text{sec}$ . Therefore, two regions from 0 to  $5\mu\text{sec}$  and from 85 to  $125\mu\text{sec}$  are the anisochronous regions. The isochronous region is divided into two dedicated  
545 regions, one (Ch. 1) from 5 to  $25\mu\text{sec}$  assigned to the first terminal and the other (Ch. 2) from 25 to  $85\mu\text{sec}$  to the third terminal.

[0075] After such assignment of the dedicated regions, the control station reports, to each station before the start of data transmission, information 40 about the dedicated regions assigned  
550 the respective terminals. When data transmission is started and

the procedure enters into the first cycle, the control station transmits a packet 41 indicating the start of the cycle to each terminal. The transmission of the cycle start packet 41 is carried out in the anisochronous region from 0 to 5  $\mu$  sec.

555 **[0076]** In response, the terminals (first and third terminals) having the isochronous data to be transmitted (I1 and I2) each transmit the isochronous data (I1 and I2) using the respective dedicated regions (channel 1 and channel 2). At this time, the third terminal divides the isochronous data I2 into three blocks  
560 (I2-1, I2-2, and I2-3) for transmission. The reason for such division will be described later.

**[0077]** After the procedure exits the isochronous region, the control station first makes an inquiry about whether or not the transmitted isochronous data (I1 and I2) has been received without  
565 error. Specifically, the control station inquires the second and fourth terminals that are the destinations of I1 and I2 about whether or not the isochronous data I1 and I2 have been successfully received. In other words, the control station first transmits an inquiry packet 42 to the second terminal, and then waits for a response  
570 packet 43 to be returned from the second terminal. Then, when the response packet 43 is returned from the second terminal, the control station then transmits an inquiry packet 44 to the fourth terminal, and waits for a response packet 45 to be returned from the fourth terminal. Then, when the response packet 45 is returned  
575 from the fourth terminal, the control station analyzes the two

response packets 43 and 45 from the second and fourth terminals to determine whether or not the isochronous data I1 and I2 have to be retransmitted. In the present example, both of the response packets indicate that the data has been successfully received.  
580 Therefore, the control station determines that no retransmission is required, and then the procedure goes to communications control for the anisochronous data.

[0078] That is, the control station gives a transmission instruction 46 to the terminal having the anisochronous data to  
585 be transmitted, that is, the fourth terminal. Upon receiving the transmission instruction 46 from the control station, the fourth terminal transmits the anisochronous data (N). The terminal that is the destination of the anisochronous data (first terminal) returns to the data originating terminal (fourth terminal) and  
590 the control station a response packet 47 indicating whether or not the data has been successfully received. In this example, the received response packet 47 indicates that the data has been successfully received. Therefore, the control station determines that no retransmission is required. Then, if any terminal having  
595 anisochronous data to be transmitted exists, the control station allows the terminal to carry out transmission, and if not, enters in a wait state.

[0079] Then, when the procedure exits the first cycle and then enters into the next cycle, the control station transmits a packet  
600 indicating the start of the next cycle to each terminal, and then



repeats the operation as describe above.

**[0080]** In the example of (B) of FIG. 1, all of the isochronous data (blocks) transmitted have been successfully received. An example case where a reception error occurs is shown in FIG. 5.

605 **[0081]** FIG. 5 is a schematic diagram for demonstrating retransmission control that is carried out when the isochronous data (block) has not been successfully received. FIG. 5 shows retransmission control that is carried out when the isochronous block I2-3 transmitted from the third terminal has not been  
610 successfully received by the fourth terminal. In this case, upon receiving an inquiry packet 50 from the control station, the fourth terminal returns a response packet 51 indicating that the isochronous block I2-3 has not been successfully received. Based on the received response packet 51, the control station determines  
615 that retransmission is required, and transmits a retransmission instruction 52 for retransmitting the isochronous block I2-3 to the third terminal. In response, the third terminal retransmits the isochronous block I2-3 to the fourth terminal.

**[0082]** Then, the control station sends a packet 53 for inquiring  
620 the fourth terminal, which is the retransmission destination of the isochronous block I2-3, about whether or not the retransmitted data has been successfully received. In this example, the fourth terminal has received the retransmitted isochronous block I2-3 without error, and therefore returns a response packet 54  
625 indicating that as such. Based on the received response packet

54, the control station determines that retransmission is not required. Then, the procedure goes to the communications control of anisochronous data.

**[0083]** As such, according to the present communications control method, when the isochronous data has not been successfully received, the isochronous data is retransmitted by using the anisochronous data region. Therefore, a transmission error of the isochronous data can be reduced without impairment of isochronous characteristics of the data.

635 **[0084]** Also, the terminal divides the isochronous data into a plurality of blocks for transmission. Therefore, if an error occurs only in part of the data, only the block where the error occurred is transmitted, thereby reducing the time which is required for retransmission. Thus, it is possible to further reduce the possibility that retransmission of the isochronous data using the anisochronous region may consume time for transmission of the anisochronous data.

**[0085]** In the example of FIG. 5, the isochronous data I2 is divided into three blocks (I2-1, I2-2, I2-3) for transmission. In general, the more the number of divisions, the lesser the possibility of consuming time for transmission of the anisochronous data. However, if the isochronous data is divided into a plurality of blocks, error detection has to be made for each block. Therefore, there is a greater number of divisions, the more the amount of processing for error detection. For this reason, it is preferable

645

650

that the number of divisions is appropriately selected in consideration of the above mentioned possibility and the amount of processing for error detection.

**[0086]** Retransmission of the anisochronous data that has not  
655 been successfully received is carried out in a similar manner to  
that of the conventional method. For example, when the response  
packet returned from the first terminal indicates that reception  
has failed, the control station transmits an instruction for  
retransmission to the fourth terminal, which is the originating  
660 terminal of the anisochronous data (N). In response, the fourth  
terminal retransmits the anisochronous data. Then, the first  
terminal, which is the destination terminal of retransmission,  
returns a response packet to the fourth terminal and the control  
station. When the response packet indicates that reception has  
665 failed, the control station again instructs the fourth terminal  
to retransmit the anisochronous data.

**[0087]** As such, the communications control method divides time  
into cycles, and each cycle has an isochronous region and  
anisochronous regions. Then, communications control of the  
670 isochronous data is carried out in the isochronous region. In  
the anisochronous region, retransmission control of the  
isochronous data that has not been successfully received is first  
carried out, and then communications control of the anisochronous  
data is executed.

675 **[0088]** Thus, a mixture of isochronous data and anisochronous

data can be serially transmitted, and a transmission error that may occur in the isochronous data can be reduced without impairment of the isochronous characteristics. Consequently, even if the rate of occurrence of transmission errors is high on the transmission path between the terminals, such as a wireless transmission path, disturbances in video during streaming reproduction and interruption in audio can be prevented.

**[0089]** Note that, in the example of FIG. 5, the retransmitted isochronous data (block I2-3) has been successfully received. However, if the retransmitted isochronous data has not again been successfully received, retransmission is repeated until a reception error is cleared (i.e., until the retransmitted isochronous data is successfully received). Alternatively, a maximum value of time used for the retransmission of the isochronous data per cycle may be predetermined. In this case, if one more retransmission operation causes the total retransmission time to exceed the maximum value, retransmission is suspended even though a reception error is not cleared. This case is illustrated in FIG. 6.

**[0090]** In general, the maximum value of the retransmission time of the isochronous data per cycle is determined so as not to exceed the time length of the anisochronous region, thereby keeping the isochronous characteristics of the isochronous data.

**[0091]** In FIG. 6, the above maximum value is set to a value which is equal to the time length of the anisochronous region (45

$\mu$  sec, for example), thereby putting reduction in a transmission error of the isochronous data as the highest priority. In the setting as shown in FIG. 6, however, anisochronous data may not possibly be transmitted at all. Therefore, in general, the maximum value is set to a value which is smaller than the time length of the anisochronous region ( $30\mu$  sec, for example).

[0092] Described next is the operation of the control station with reference to a flowchart. FIG. 7 is a flowchart showing the operation of the control station 10 of FIG. 2. In FIG. 7, the control station first divides time into cycles, and sets, in each cycle, an isochronous region and anisochronous regions (step S1). Then, the maximum time used for retransmission of the isochronous data in each cycle is set (step S2). This maximum value is set to a value that does not exceed the time length of the anisochronous region. Furthermore, the maximum number of times of retransmission, indicating how many times retransmission of the same isochronous data can be allowed, is set (step S3). The maximum number of times of retransmission will be described in detail later.

[0093] The control station then divides the isochronous region set in step S1 into a plurality of dedicated regions, and assigns the dedicated regions to respective terminals (step S4). The control station then reports information about the assigned dedicated region to each terminal before the start of transmission (step S5). A timing of each terminal transmitting the isochronous data is described in the dedicated region information. An example

of the dedicated region information is illustrated in FIG. 8

**[0094]** As shown in FIG. 8, transmission times of respective isochronous data blocks are described in the dedicated region information packet.

730 **[0095]** Following step S5, the control station reports the start of the cycle to each terminal (step S6). In response, each terminal transmits its own isochronous data using the assigned dedicated region.

**[0096]** Then, the control station determines whether or not the  
735 isochronous data transmitted from each terminal has been successfully received by the destination terminal (step S7). If Yes, the procedure goes to step S11.

**[0097]** If No in step S7, the control station further determines whether one or more retransmission operation(s) in the cycle causes  
740 the total retransmission time to exceed the maximum value set in step S2 (step S8). If Yes, the control station suspends retransmission, and goes to step S11.

**[0098]** If No in step S8, the control station determines whether or not the number of times of retransmission of the isochronous  
745 data that has not been successfully received reaches the maximum number of times of retransmission set in step S3 (step S9). If Yes, the procedure returns to step S7, and repeats the above processing.

**[0099]** If No in step S9, the control station instructs the data  
750 originating terminal to retransmit the isochronous data that has

not been successfully received (step S10). In response, the data originating terminal retransmits the isochronous data by using the anisochronous region. The procedure then returns to step S7, and repeats the above processing.

755 [0100] In step S11, the control station carries out transmission control on the anisochronous data until the procedure reaches at the end of the anisochronous region.

[0101] In the next step S12, it is determined whether or not the current cycle is the last one. If Yes, the operation of the  
760 control station ends.

[0102] If No in step S12, the procedure returns to step S6, where the control station reports the start of the next cycle to each terminal, and then repeats the above processing.

[0103] Described next is the operation of the terminal. FIG. 9  
765 is a flowchart showing the operation of each of the terminals 11 to 14 shown in FIG. 2. In FIG. 9, the terminal first determines whether or not it has isochronous data to be transmitted (step S21). If No, the procedure goes to step S23.

[0104] If Yes in step S21, the terminal transmits the  
770 isochronous data (step S22). Then, the terminal determines whether or not it has anisochronous data to be transmitted (step S23). If No, the procedure goes to step S25.

[0105] If Yes in step S23, the terminal transmits the anisochronous data (step S24), and then the procedure goes to step  
775 S25. Note that the transmitted anisochronous data has an error

detection code added thereto.

[0106] In step S25, the terminal determines whether or not it has to receive any data. If Yes, the terminal executes a data reception operation (step S26), and then the procedure goes to  
780 step S27. If No in step S25, the procedure skips step S26 to go to step S27.

[0107] In step S27, it is determined whether or not to continue the operation. If Yes, the procedure ends. If No, the procedure returns to step S21, and repeats the above processing.

785 [0108] FIG. 10 is a flowchart showing the detailed processing of transmitting the isochronous data shown in step S22 of FIG. 9. In FIG. 10, the terminal first receives a report about the dedicated region information from the control station (step S41). Then, the terminal waits for a report indicating the start of the cycle  
790 (step S42).

[0109] After being notified of the start of the cycle, the terminal transmits the isochronous data by using the assigned dedicated region (step S43). That is, the terminal transmits the isochronous data at the time described in the dedicated region  
795 information received in step S41. Note that the transmitted isochronous data has an error detection code added thereto.

[0110] Then, the terminal determines whether or not it has been instructed by the control station to retransmit the isochronous data (step S44). If No, the procedure returns to the flow of FIG. 9,  
800 and goes to step S23.



[0111] If Yes in step S44, the terminal retransmits the isochronous data using the anisochronous region (step S45). Note that the retransmitted isochronous data has an error detection code added thereto. The procedure then returns to the flow of  
805 FIG. 9, and goes to step S23. These are the details of step S22.

[0112] FIG. 11 is a flowchart showing the detailed processing of data reception shown in step S26 of FIG. 9. In FIG. 11, the terminal first receives data that is destined thereto (step S61). The terminal then checks whether or not the received data has any  
810 error (step S62). This check can be done based on the error detection code added to the received data.

[0113] The terminal then transmits a response packet including the check result obtained in step S62 to the control station (step S63). The procedure then returns to the flow of FIG. 9, and goes  
815 to step S27. An example structure of the response packet is shown in FIG. 12.

[0114] As shown in FIG. 12, a state of reception of the isochronous data (the presence or absence of an error) for each block is described in the response packet.

820 [0115] Note that, the isochronous data whose retransmission is suspended based on the determination in step S8 that a further retransmission operation will exceed the maximum value is retransmitted in the anisochronous region of the next cycle. This is shown in FIG. 13. In FIG. 13, retransmission of the isochronous  
825 data I1 is once suspended at the end of the cycle 61, and is then

restarted after the procedure enters into the anisochronous region of the next cycle 62.

[0116] However, repetitive retransmission of the same isochronous data may consume time for retransmitting other  
830 isochronous data. To get around this problem, the number of times of retransmission of the same data is limited to not more than a predetermined number (two, for example). This is the maximum number of times of retransmission set in step S3. In the example of FIG. 13, even though the second retransmission using the  
835 anisochronous region of the next cycle 62 has not cleared the transmission error, the third retransmission is not performed because the number of times of retransmission of the same data is limited to not more than two.

[0117] Here, to reduce the number of times of retransmission,  
840 when instructing the originating terminal to retransmit the isochronous data that has not been successfully received, the control station may also instruct the originating terminal to change the modulation scheme and/or the coding rate.

[0118] Specifically, before transmitting the isochronous data,  
845 each terminal encodes the data at a predetermined coding rate, and then modulates the encoded data in a predetermined scheme. If the modulation scheme used for transmission is changed at retransmission, the possibility of the occurrence of transmission errors can be reduced, as compared with the case where the same  
850 modulation scheme is used for retransmission. If the coding rate

used for transmission is also changed at retransmission, the possibility of the occurrence of transmission errors can be further reduced. Consequently, the number of times of retransmission can be reduced, and the possibility that repetitive retransmission  
855 may consume time for transmitting anisochronous data can be further reduced.

**[0119]** In the first embodiment, each terminal transmits the isochronous data to a single terminal. Alternatively, each terminal may carry out multicast transmission, where each terminal  
860 transmits the isochronous data to a plurality of terminals of respective specific groups. Still alternatively, each terminal may carry out broadcast transmission, where each terminal transmits the isochronous data to all of the other terminals. Described in a second embodiment below is communications control when each  
865 terminal carries out multicast or broadcast transmission of isochronous data.

**[0120] Second Embodiment**

FIG. 14 is a schematic diagram for demonstrating a communications control method according to the second embodiment  
870 of the present invention. One example structure of a wireless local area network to which the method of FIG. 14 is applied is similar to that shown in FIG. 2. The structure of the wireless communications module 20 equipped in the control station and each terminal shown in FIG. 2 is similar to that shown in FIG. 3. The  
875 contents of the program memory 24 of FIG. 3 are similar to those

shown in FIG. 4, except that the control station program 31 and the terminal program 32 are partly different from those according to the first embodiment.

**[0121]** In the example of FIG. 14, in a single isochronous region,  
880 the first terminal carries out broadcast transmission of three isochronous blocks (I1-1, I1-2, and I1-3) to the second to fourth terminals. Here, if many terminals other than those shown in the drawing exist and the second to fourth terminals belong to a single group, the first terminal is regarded as carrying out multicast  
885 transmission to the terminals that belong to the group.

**[0122]** As shown in FIG. 14, the second terminal has successfully received the blocks I1-2 and I1-3, but has not successfully received the block I1-1. The third terminal has successfully received the blocks I1-1, I1-2, and I1-3. The fourth terminal has successfully  
890 received the blocks I1-1 and I1-2, but has not successfully received the block I1-3.

**[0123]** In the anisochronous region, the control station sequentially transmits inquiry packets 70 to 72 for inquiring the destination stations (the second to fourth terminals) about whether  
895 or not they have successfully received the isochronous data. Upon sequentially receiving response packets 73 to 75 from the second to fourth terminals, the control station sequentially transmits, to the data originating station (the first terminal), packets 76 and 77 for instructing retransmission of the isochronous blocks  
900 that have not been successfully received (I1-1 and I1-3).

[0124] In response, the first terminal carries out broadcast retransmission of the blocks I1-1 and I1-3 to the second to fourth terminals. Then, the control station sequentially transmits packets 78 and 79 for inquiring the second and fourth terminals, 905 which have not successfully received the blocks I1-1 and I1-3, respectively, about whether or not they have received the respective retransmitted blocks. Then, after the control station receives, from the second and fourth terminals, response packets 80 and 81 each indicating that the retransmitted block has been 910 successfully received, the retransmission processing ends.

[0125] The operation of the control station is similar to that shown in FIG. 7. However, in the case of multicast transmission where each terminal transmits the isochronous data to a plurality of terminals that belong to respective specific groups, the control 915 station determines in step S7 whether or not the isochronous data has been successfully received by all terminals that belong to one group. Then, if there is any terminal in that group which has not successfully received the isochronous data, multicast retransmission of the isochronous data to all terminals in the 920 group is carried out.

[0126] On the other hand, if each terminal carries out broadcast transmission of the isochronous data to all of the other terminals, the control station determines in step S7 whether the isochronous data has been successfully received by all of the terminals. Then, 925 if there is any terminal that has not successfully received the

isochronous data, broadcast retransmission of the isochronous data to all destination terminals is carried out.

[0127] In the first embodiment, the control station sequentially inquires the destination terminals about whether or  
930 reception has succeeded. Such inquiries to these terminals can be made in a collective manner. Also, in the first embodiment, upon receiving responses each indicating a reception error from many terminals, the control station sequentially gives retransmission instructions to the respective terminals that have  
935 not successfully received the isochronous data. Such retransmission instructions can be made in a collective manner. Described in a third embodiment below is a communications control method which is capable of giving the respective terminals a global inquiry about whether or not reception has succeeded and a global  
940 retransmission instruction.

**[0128] Third Embodiment**

FIG. 15 is a schematic diagram for demonstrating a communications control method according to the third embodiment of the present invention. An example of the structure of a wireless  
945 local area network to which the method of FIG. 15 is applied is similar to that in FIG. 2 with a fifth terminal (another computer, for example) newly added thereto. The structure of the wireless communications module 20 equipped to the control station and each terminal of FIG. 2 is similar to that shown in FIG. 3. The contents  
950 of the program memory 24 of FIG. 3 are similar to those shown in

FIG. 4, except that the control terminal program 31 and the terminal program 32 are partly different from those according to the first embodiment.

**[0129]** FIG. 15 shows an example of retransmission control in which inquiries about whether or not reception has succeeded and retransmission instructions are made in a collective manner. In FIG. 15, in the isochronous region, multicast transmission of two isochronous blocks (I1-1 and I1-2) is first carried out from the first terminal to the second and third terminals. Then, multicast transmission of one isochronous block (I2-1) is carried out from the fourth terminal to the third and fifth terminals. In the anisochronous region, the control station first carries out multicast transmission of a packet 90 that includes inquiries to the second, third, and fifth terminals about whether or not reception has succeeded. The contents of the global inquiry packet 90 are shown in FIG. 16.

**[0130]** As shown in FIG. 16, the global inquiry packet 90 describes address of the terminals that should transmit a response packet indicating whether or not reception has succeeded (that is, the second, third, and fifth terminals, which are the destination terminals of the isochronous blocks), "2", "3", and "5", addresses of the terminals that should receive the response packet (that is, the first and fourth terminals, which are the originating terminals of the isochronous blocks), "1" and "4", and times when the response packets should be transmitted, "t1"

to "t4".

[0131] Referring back to FIG. 15, when receiving the global inquiry packet 90 as shown in FIG. 16, the second, third, and fifth terminals, which are the destination terminals of the isochronous blocks, transmit response packets 91 to 94 at the respective specified times to the control station and the respective specified terminals.

[0132] More specifically, in the example shown in FIGS. 15 and 16, the second terminal transmits, at the time "t1", the response packet 91 indicating a reception error of the isochronous block I1-1 and successful reception of the isochronous block I1-2 to the control station and the first terminal.

[0133] Then, the third terminal transmits, at the time "t2", the response packet 92 indicating successful reception of two isochronous blocks I1-1 and I1-2 to the control station and the first terminal. Furthermore, the third terminal transmits, at the time "t3", the response packet 93 indicating a reception error of the isochronous block I2-1 to the control station and the fourth terminal.

[0134] Then, the fifth terminal transmits, at the time "t4", the response packet 94 indicating successful reception of the isochronous block I2-1 to the control station and the fourth terminal.

[0135] When receiving the response packets 91 to 94 from the second, third, and fifth terminals, the control station carries



out multicast transmission of a packet 95 for instructing, in a global manner, the originating terminals (first and fourth terminals) to retransmit the isochronous blocks (I1-1 and I2-1) that have not been successfully received. The contents of the  
1005 global retransmission packet 95 are shown in FIG. 17.

[0136] As shown in FIG. 17, the global retransmission instruction packet 95 describes addresses of the terminals that should execute retransmission (first and fourth terminals), "1" and "4", groups that should receive the isochronous data  
1010 retransmitted by the terminals, "group 1" and "group 2", and times when retransmission should be executed, "t5" and "t6". Here, "group 1" includes the second and third terminals, and "group 2" includes the third and fifth terminals.

[0137] Referring back to FIG. 15, when receiving the global  
1015 retransmission instruction packet 95 as shown in FIG. 17, the first and fourth terminals carry out multicast retransmission of the respective isochronous blocks at the respective specific times to the terminals included in the specified group. That is, the first terminal carries out, at the time "t5", multicast  
1020 retransmission of the isochronous block I1-1 to the second and third terminals included in "group 1". The fourth terminal carries out, at the time "t6", multicast retransmission of the isochronous block I2-1 to the third and fifth terminals included in "group 2".

[0138] Then, the control station carries out multicast  
1025 transmission of a global inquiry packet 96 for inquiring the second

and third terminals, which are the destination terminals, whether or not reception has succeeded. In response, the second terminal first transmits a response packet 97 indicating successful reception to the control station and the first terminal. Then,  
1030 the third terminal transmits a response packet 98 indicating successful reception to the control station and the fourth terminal.

**[0139]** In the first embodiment, the control station inquires each of the terminals, which are the destination terminals of the  
1035 isochronous data, about whether or not reception has succeeded. In response, each terminal transmits a response packet. Alternatively, each terminal may spontaneously transmit a response packet upon reception of the isochronous data. Described in a  
1040 each terminal spontaneously transmits a response packet upon reception of the isochronous data.

**[0140]** Fourth Embodiment

FIG. 18 is a schematic diagram for demonstrating a communications control method according to the fourth embodiment  
1045 of the present invention. An example structure of a wireless local area network to which the method of FIG. 18 is applied is similar to that shown in FIG. 2. The structure of the wireless communications module 20 equipped to the control station and each terminal of FIG. 2 is similar to that shown in FIG. 3. The contents  
1050 of the program memory 24 are similar to those shown in FIG. 4,

except that the control station program 31 and the terminal program 32 are partly different from those in the first embodiment.

1055 [0141] In FIG. 1, in the anisochronous region, the control station transmits the inquiry packets 42 and 44 to the second and fourth terminals, which are the destination terminals of the isochronous data I1 and I2, respectively. In response to the inquiry, the second and fourth terminals transmit the response packets 43 and 45, respectively.

1060 [0142] On the other hand, in FIG. 18, the destination terminal of the isochronous block (the fourth terminal) spontaneously transmits response packets 100 to 102 upon reception of the isochronous blocks (I2-1, I2-2, and I2-3). Therefore, the control station does not have to make inquiries in the anisochronous region about whether or not reception has succeeded. Other than the above, 1065 FIG. 18 is similar to FIG. 1.

[0143] In the first embodiment, the control station reports the dedicated region information to each terminal before the start of transmission. Each terminal transmits the isochronous data at the time described in the reported information. Alternatively, 1070 the control station may sequentially instruct the respective terminals about transmission and, in response, each terminal may transmit the isochronous data. Described in a fifth embodiment below is a communication control method of sequentially instructing the respective terminals to transmit the isochronous data.

1075 [0144] Fifth Embodiment

FIG. 19 is a schematic diagram for demonstrating a communications control method according to the fifth embodiment of the present invention. An example of the structure of a wireless local area network to which the method of FIG. 19 is applied is similar to that shown in FIG. 2. The structure of the wireless communications module 20 is similar to that in FIG. 3. The contents of the program memory 24 of FIG. 3 are similar to those shown in FIG. 4, except that the control station program 31 and the terminal program 32 are partly different from those according to the first embodiment.

**[0145]** In FIG. 1, the control station reports the dedicated region information 40 to each terminal before the start of transmission. Each terminal executes transmission of the isochronous data at the time described in the reported information (refer to the first embodiment). On the other hand, in FIG. 19, the control station sequentially transmits transmission instructions to the respective terminals at the times corresponding to the respective dedicated regions. In response, the terminals transmit the isochronous block one after the other.

**[0146]** More specifically, the control station transmits a transmission instruction 110 to the first terminal in timing corresponding to Ch. 1. In response, the first terminal transmits an isochronous block 11. Then, the control station transmits transmission instructions 111, 112, and 113 to the third terminal in timing corresponding to channel 2. In response, the third

terminal sequentially transmits isochronous blocks I2-1, I2-2, and I2-3. Other than the above, FIG. 19 is similar to FIG. 1.

1105 [0147] The processing that is carried out when the isochronous data (block) has not been successfully received is similar to that shown in FIG. 5 (refer to the first embodiment).

[0148] FIG. 20 is a flowchart showing the operation of the control station. The flowchart of FIG. 20 is similar to that of FIG. 7 (refer to the first embodiment), except for the following point. Specifically, in FIG. 7, the control station reports the  
1110 information about the dedicated region assigned in step S4 to each terminal before the start of transmission (step S5), and then reports the start of the cycle to each terminal (step S6). On the other hand, in FIG. 20, after executing step S4, the control station skips step S5 to execute step S6.

1115 [0149] After reporting the start of the cycle to each terminal in step S6, the control station sequentially instructs the respective terminals to transmit the isochronous data at the time corresponding to the dedicated region assigned in step S4 (step S101). In response to the instruction, each of the terminals  
1120 sequentially transmits the isochronous data. Then, the procedure goes to step S7 and thereafter.

[0150] The operation of each terminal is similar to that according to the first embodiment, which is shown in the flowchart of FIG. 9. The details on the data receiving processing shown  
1125 in step S26 of FIG. 9 are similar to those according to the first

embodiment, which are shown in the flowchart of FIG. 10. However, the details on step S22 are partly different from that according to the first embodiment, which are described below.

**[0151]** FIG. 21 is a flowchart showing the details on the isochronous data transmission processing shown in step S22 of FIG. 9. The flowchart of FIG. 21 is similar to that of FIG. 10 (refer to the first embodiment) except for the following. That is, in FIG. 10, the terminal first receives a report of the dedicated region information from the control station (step S41), and waits for a report of the start of the cycle (step S42). After being informed of the start of the cycle, the terminal transmits the isochronous data by using the assigned dedicated region (step S43).

**[0152]** On the other hand, in FIG. 21, step S41 is skipped. The terminal first executes step S42. Then, after being notified of the start of the cycle, the terminal enters in a wait state, waiting for a transmission instruction (step S121). After receiving a transmission instruction from the control station, the terminal transmits the isochronous data (step S122). Then, the procedure goes to step S144 and thereafter.

**[0153]** In the fifth embodiment, the control station inquires each destination terminal of the isochronous data about whether or not reception has succeeded. In response, each terminal transmits a response packet. Alternatively, each terminal may spontaneously transmit a response packet upon receipt of the isochronous data. A communications control method used in such

a case is shown in FIG. 22.

[0154] In FIG. 22, upon receiving the isochronous data (I2-1, I2-2, and I2-3), the fourth terminal transmits response packets 120, 121, and 122, respectively. Therefore, the control station  
1155 does not have to make inquiries about whether or not reception has succeeded in the anisochronous region.

[0155] While the present invention has been described in detail, the foregoing description is in all aspects illustrative and not restrictive. It is understood that numerous other modifications  
1160 and variations can be devised without departing from the scope of the invention.